



## PR-80C

- Support 10,000 users.
- Built-in RS232 & RS485 interface.
- Frequency is 125KHZ.
- Reading range from 10~16cm



Feature

Specification

Order Info

Relevant Products

### ▣ Feature

- Standalone or PC on line with JAS software.
- Frequency is 125KHZ.
- With backlit LCD display.
- Programmable door delay close time from 0~255 seconds, when door unlock over delay time setting, the alarm signal will output.
- Support 10,000 users.
- Can be used by 1.8mm、0.76mm EM card or key tag.
- Reading range from 10~16cm (under normal environment).
- Built-in clock and calendar.
- Built-in RS232 & RS485 interface.
- Can save 10,000 door access history record.
- Built-in Watch Dog, the system never hang.
- Built-in tamper switch detects when case is forced open or destroy, the alarm signal output (A. B. point).
- Data is protected even after power failure.
- With 60 holiday setting function (Option device).
- There are three different schedules in each day for user to set special time schedule.
- Inside door can be installed a push button or PR-200/PR-300.
- With real-time printing function (RS232 port), can be connected a serial printer.
- Operation mode: Card Only, Card + PIN, PIN or Card, Facility Code Only, Opening or Inhibit Access.
- Intranet network with TCP/IP Converter (option device)
- Built-in Mifare/HID module (option device)

### ▣ Specification

Display	2X16 Characters (backlit LCD)
Keypad	4 x 4 16 Keys
Operating Environment Temperature	0~50 °C
Humidity	20%~90% RH
Dimensions	147 (L) X 119 (W) X 40 (H) mm
Power	DC 12V 1Amp
Relay	2 relay contact (Max.. DC 12V, 1Amp)